

## Claims

I claim:

- 5  
SUB  
PAT
1. First-arriving pulse detector circuitry, comprising:  
a correlator circuitry configured to correlate a received signal with a template signal to provide an output signal; and  
a threshold circuitry configured to provide a first-arriving-pulse signal depending on the relative values of the output signal of the correlator circuitry and a threshold signal.
2. The circuitry of claim 1, in which the received signal is received via a multipath propagation medium.
3. The circuitry of claim 2, in which the correlator circuitry further comprises:  
a multiplier circuitry configured to provide an output signal that comprises the product of the template signal and the received signal; and  
an integrator circuitry configured to integrate the output signal of the multiplier circuitry to provide the output signal of the correlator circuitry.
4. The circuitry of claim 3, in which the threshold circuitry further comprises a comparator circuitry configured to compare the output signal of the correlator circuitry with the threshold signal to provide the first-arriving-pulse signal.

Sub  
AA

5. The circuitry of claim 4, in which the first-arriving-pulse signal tends to indicate the time position of a first pulse in the received signal.

5 6. The circuitry of claim 5, in which the received signal comprises an ultra-wideband signal.

7. The circuitry of claim 6, in which the threshold signal comprises a first number added to the product of a second number and a third number.

Sub  
A3

8. The circuitry of claim 7, in which the first number comprises the average of a noise floor, the second number comprises the standard deviation of the noise floor, and the third number comprises a scaling factor.

9. The circuitry of claim 8, in which the template signal comprises a limited-size template signal.

10. The circuitry of claim 8, in which the template signal comprises a discrete-time signal.

Sub  
A4

11. A radio-frequency (RF) apparatus comprising:  
a radio-frequency circuitry configured to receive a plurality of pulses that result from a transmission of a radio-frequency pulse in a multipath propagation medium; and

a detector circuitry configured to discriminate from a noise a first pulse in the plurality of pulses.

12. The apparatus of claim 11, in which the detector circuitry further comprises a correlator  
5 circuitry configured to correlate the plurality of pulses with a template signal to provide an output signal.

13. The apparatus of claim 12, in which the detector circuitry further comprises a threshold  
circuitry configured to provide a first-arriving-pulse signal by comparing the output signal of the  
correlator circuitry to a threshold signal.

14. The apparatus of claim 13, in which the detector circuitry is further configured to provide  
a first-arriving-pulse signal that tends to indicate the time position of the first pulse in the  
plurality of pulses.

15. The apparatus of claim 14, in which the radio-frequency pulse transmitted in the  
multipath propagation medium comprises an ultra-wideband signal.

16. The circuitry of claim 15, in which the threshold signal comprises a first number added to  
20 the product of a second number and a third number.

17. The circuitry of claim 16, in which the first number comprises the average of the noise floor, the second number comprises the standard deviation of the noise floor, and the third number comprises a scaling factor.

18. The circuitry of claim 17, in which the template signal comprises a limited-size template signal.

19. The circuitry of claim 17, in which the template signal comprises a discrete-time signal.

20. A communication system, comprising:  
a transmitter circuitry configured to transmit a radio-frequency pulse into a multipath propagation medium;  
a receiver circuitry configured to receive a plurality of pulses that result from the transmission of the pulse into the multipath propagation medium; and  
a detector circuitry configured to detect the first pulse of the plurality of pulses.

21. The system of claim 20, in which the detector circuitry further comprises a correlator circuitry configured to correlate the plurality of pulses with a template signal to provide an output signal.

22. The system of claim 21, in which the detector circuitry further comprises a threshold circuitry configured to provide a first-arriving-pulse signal by comparing the output signal of the correlator circuitry to a threshold signal.

23. The system of claim 22, in which the receiver circuitry comprises a scanning receiver circuitry.

24. The system of claim 23, in which the radio-frequency pulse transmitted in the multipath propagation medium comprises an ultra-wideband signal.

25. The system of claim 24, in which the threshold signal comprises a first number added to the product of a second number and a third number.

26. The system of claim 25, in which the first number comprises the average of the noise floor, the second number comprises the standard deviation of the noise floor, and the third number comprises a scaling factor.

27. The system of claim 26, in which the detector circuitry is further configured to provide a first-arriving-pulse signal that tends to indicate the time position of the first pulse in the plurality of pulses.

28. The system of claim 27, in which the transmitter circuitry, the receiver circuitry, and the detector circuitry reside within a radar circuitry.

29. The system of claim 28, in which the receiver circuitry couples to a processor circuitry.

5

30. The system of claim 29, in which the detector circuitry resides within the processor circuitry.

31. The system of claim 28, in which the detector circuitry resides within the receiver circuitry.

32. The system of claim 27, in which the detector circuitry resides within a processor coupled to the receiver circuitry.

15

33. The system of claim 27, in which the detector circuitry resides within the receiver circuitry.

34. The system of claim 33, in which the receiver circuitry couples to a processor circuitry.

20

35. The system of claim 27, in which the detector circuitry resides within a first transceiver circuitry.

36. The system of claim 35, in which the receiver circuitry resides within the first transceiver circuitry.

37. The system of claim 36, in which the detector circuitry resides within the first transceiver circuitry.

38. The system of claim 37, in which the transmitter circuitry resides within a second transceiver circuitry.

39. The system of claim 38, in which the receiver circuitry couples to a processor circuitry.

40. The system of claim 39, in which the detector circuitry resides within the processor circuitry.

41. The system of claim 40, in which the detector circuitry resides within the receiver circuitry.

42. A method of detecting a first-arriving pulse, comprising:

correlating a received signal with a template signal by to provide a correlation output signal; and

comparing the correlation output signal and a threshold signal to provide a first-arriving-pulse signal.

43. The method of claim 42, in which the received signal is received in a multipath propagation medium.

5 44. The method of claim 43, in which correlating the received signal and the template signal further comprises:

multiplying the template signal and the received signal to provide a product signal; and  
integrating the product output signal to provide the correlation output signal.

45. The method of claim 44, in which comparing the correlation output signal and a threshold signal further comprises using a comparator circuitry configured to compare the correlation output signal and the threshold signal to provide the first-arriving-pulse signal.

Sub  
A9  
15 46. The method of claim 45, in which the first-arriving-pulse signal tends to indicate the time position of a first pulse in the received signal.

47. The method of claim 46, in which the received signal comprises an ultra-wideband signal.

48. The method of claim 47, in which the threshold signal comprises a first number added to  
20 the product of a second number and a third number.



Sub A10 49. The method of claim 48, in which the first number comprises the average of a noise floor, the second number comprises the standard deviation of the noise floor, and the third number comprises a scaling factor.

5 50. The method of claim 49, in which the template signal comprises a limited-size signal.

51. The method of claim 49, in which the template signal comprises a discrete-time signal.

Sub A11 52. A method of detecting a first pulse among a plurality of pulses, comprising:  
transmitting a radio-frequency pulse in a multipath propagation medium;  
receiving, by using a radio-frequency circuitry, the plurality of pulses that result from the  
transmission of the radio-frequency pulse; and  
discriminating, by using a detector circuitry, a first pulse in the plurality of pulses from a  
noise floor.

53. The method of claim 52, in which using the detector circuitry further comprises  
correlating the plurality of pulses with a template signal to provide an correlation output signal.

20 54. The method of claim 53, which further comprises including within the detector circuitry a  
threshold circuitry configured to provide a first-arriving-pulse signal by comparing the  
correlation output signal to a threshold signal.

55. The method of claim 54, which further comprises using the detector circuitry to provide a first-arriving-pulse signal that tends to indicate the time position of the first pulse in the plurality of pulses.

56. The method of claim 55, in which the radio-frequency pulse transmitted in the multipath propagation medium comprises an ultra-wideband signal.

57. The method of claim 56, in which the threshold signal comprises a first number added to the product of a second number and a third number.

58. The method of claim 57, in which the first number comprises the average of the noise floor, the second number comprises the standard deviation of the noise floor, and the third number comprises a scaling factor.

59. The method of claim 58, in which the template signal comprises a limited-size signal.

60. The method of claim 58, in which the template signal comprises a discrete-time signal.